

FAQ about ESC/POS®

All rights reserved. No part of this publication may be reproduced, stored in a retrieval system, or transmitted in any form or by any means, electronic, mechanical, photocopying, recording, or otherwise, without the prior written permission of Seiko Epson Corporation. No patent liability is assumed with respect to the use of the information contained herein. While every precaution has been taken in the preparation of this book, Seiko Epson Corporation assumes no responsibility for errors or omissions. Neither is any liability assumed for damages resulting from the use of the information contained herein.

Neither Seiko Epson Corporation nor its affiliates shall be liable to the purchaser of this product or third parties for damages, losses, costs, or expenses incurred by purchaser or third parties as a result of: accident, misuse, or abuse of this product or unauthorized modifications, repairs, or alterations to this product, or (excluding the U.S.) failure to strictly comply with Seiko Epson Corporation's operating and maintenance instructions.

Seiko Epson Corporation shall not be liable against any damages or problems arising from the use of any options or any consumable products other than those designated as Original EPSON Products or EPSON Approved Products by Seiko Epson Corporation. The contents of this document are covered by one or more of patents.

EPSON and ESC/POS[®] are registered trademarks of Seiko Epson Corporation.

NOTICE: The contents of this manual are subject to change without notice.

Copyright © 2002 by Seiko Epson Corporation, Nagano, Japan.

FAQ about ESC/POS[®]

- 1 What is ESC/POS? 1
- 2 Applicable printer models 2
- 3 Command Notation 2
 - 3.1 Control Commands 3
- 4 Sample Program (Basic) 11
- 5 Serial Connection 12
- 6 Self-test Mode 12

***T* What is ESC/POS?**

EPSON took the initiative by introducing ESC/POS[®], a proprietary POS printer command system, which includes patented or patent pending commands and enables versatile POS system construction with high scalability. Compatible with all types of EPSON POS printers and displays, this proprietary control system also offers the flexibility to easily make future upgrades. Its popularity is worldwide.

ESC/POS[®] is designed to reduce the processing load on the host computer in POS environments. It comprises a set of highly functional and efficient commands that enables the full realization of the potential of printers.

A command set designed for universal applicability

The commands that are supported by all EPSON POS printers and those that are specific to individual models are clearly described. This means that ESC/POS[®] compatible software will work with any system and be suitable for a wide range of applications.

Superb expandability allowing the addition of new functions

New functions can be added and accommodated by the categories already provided in the command system.

Allows more effective use of software

Once a software application has been created for one printer in the TM series, it can be used as the basis for versions for the other printers in the series. Only a small portion of the program source code needs to be modified.

If you would like to get more information about ESC/POS[®] commands, contact the dealer where you purchased the product to get the ESC/POS[®] Application Programming Guide (ESC/POS[®] APG).

2 Applicable printer models

This FAQ is for TM-T90, TM-L90, TM- T88III, TM-J2000/2100, TM-L60II, TM-U200, and TM-U230. These printers support commands which are described in this FAQ as shown in the following table.

Command	Name	TM-T90	TM-L90	TM-T88III TM-T88II	TM-J2000/2100	TM-L60II	TM-U200 series	TM-U230
LF	Print and line feed	✓	✓	✓	✓	✓	✓	✓
ESC !	Select print mode(s)	✓	✓	✓	✓	✓	✓	✓
ESC –	Turn underline mode on/off	✓	✓	✓	✓	✓	✓	✓
ESC @	Initialize printer	✓	✓	✓	✓	✓	✓	✓
ESC E	Turn emphasized mode on/off	✓	✓	✓	✓	✓	✓	✓
ESC G	Turn double-strike mode on/off	✓	✓	✓	✓	✓	✓	✓
ESC M	Select character font	✓	✓	✓	✓	--	--	--
ESC a	Select justification	✓	✓	✓	✓	✓	✓	✓
ESC c 3	Select paper sensor(s) to output paper-end signals	✓	✓	✓	✓	✓	✓	✓
ESC d	Print and feed n lines	✓	✓	✓	✓	✓	✓	✓
ESC e	Print and reverse feed n lines	--	--	--	--	--	✓	✓
ESC p	General pulse	✓	✓	✓	✓	✓	✓	✓
ESC r	Select print color	--	--	--	✓	--	✓	✓
ESC t	Select character code table	✓	✓	✓	✓	✓	✓	✓
GS B	Turn white/black reverse printing mode on/off	✓	✓	✓	✓	✓	✓	✓
GS V	Select cut mode and cut paper	✓	✓	✓	✓	--	✓	✓
GS h	Set bar code height	✓	✓	✓	✓	✓	--	--
GS k	Print bar code	✓	✓	✓	✓	✓	--	--

3 Command Notation

- [Name] The name of the command.
- [Format] The code sequence.
 []*k* indicates the contents of the [] should be repeated *k* times.
- [Range] Gives the allowable ranges, if any, for the arguments.
- [Default] Gives the default values, if any, for the command parameters.
- [Description] Describes the function of the command.

3.1 Control Commands

LF

[Name] Print and line feed

[Format] ASCII LF
Hex 0A
Decimal 10

[Description] Prints the data in the print buffer and feeds one line based on the current line spacing.

ESC ! *n*

[Name] Select print mode (*s*)

[Format] ASCII ESC ! *n*
Hex 1B 21 *n*
Decimal 27 33 *n*

[Range] $0 \leq n \leq 255$

[Default] $n = 0$

[Description] Selects the character font and styles (emphasize, double-height, double-width, and underline) together.

Bit	Off/On	Hex	Decimal	Function
0	Off	00	0	Character font A selected.
	On	01	1	Character font B selected.
1, 2	Off	00	0	Reserved.
3	Off	00	0	Emphasized mode not selected.
	On	08	8	Emphasized mode selected.
4	Off	00	0	Double-height mode not selected.
	On	10	16	Double-height mode selected.
5	Off	00	0	Double-width mode not selected.
	On	20	32	Double-width mode selected.
6	Off	00	0	Reserved.
7	Off	00	0	Underline mode not selected.
	On	80	128	Underline mode selected.

ESC – *n*

[Name] Turn underline mode on/off
[Format] ASCII ESC – *n*
Hex 1B 2D *n*
Decimal 27 45 *n*
[Range] $0 \leq n \leq 2, 48 \leq n \leq 50$
[Default] $n = 0$
[Description] Turns underline mode on or off, based on the following values of *n*:

n	Function
0, 48	Turns off underline mode
1, 49	Turns on underline mode, set at 1-dot width
2, 50	Turns on underline mode, set at 2-dot width



Note:

For the TM-U230 or TM-U210, the range is $n = 0, 1, 48, 49$

ESC @

[Name] Initialize printer
[Format] ASCII ESC @
Hex 1B 40
Decimal 27 64
[Description] Clears the data in the print buffer and resets the printer modes to the modes that were in effect when the power was turned on.

ESC E *n*

[Name] Turn emphasized mode on/off
[Format] ASCII ESC E *n*
Hex 1B 45 *n*
Decimal 27 69 *n*
[Range] $0 \leq n \leq 255$
[Default] $n = 0$
[Description] Turns emphasized mode on or off.

- When the LSB of *n* is 0, emphasized mode is turned off.
- When the LSB of *n* is 1, emphasized mode is turned on.

ESC G *n*

[Name] Turn double-strike mode on/off

[Format] ASCII ESC G *n*
Hex 1B 47 *n*
Decimal 27 71 *n*

[Range] $0 \leq n \leq 255$

[Default] $n = 0$

[Description] Turns double-strike mode on or off.

- When the LSB of *n* is 0, double-strike mode is turned off.
- When the LSB of *n* is 1, double-strike mode is turned on.

ESC M *n*

[Name] Select character font

[Format] ASCII ESC M *n*
Hex 1B 4D *n*
Decimal 27 77 *n*

[Range] $0 \leq n \leq 2, 48 \leq n \leq 50$

[Default] $n = 0$

[Description] Selects character fonts

n	Function
0, 48	Character font A selected.
1, 49	Character font B selected.
2, 50	Character font C selected.



Note:

Some printers don't have font C. See the ESC/POS[®] Application Programming Guide (ESC/POS[®] APG).

ESC a *n*

[Name] Select justification

[Format] ASCII ESC a *n*
Hex 1B 61 *n*
Decimal 27 97 *n*

[Range] $0 \leq n \leq 2, 48 \leq n \leq 50$

[Default] $n = 0$

[Description] Aligns all the data in one line to the position specified by *n* as follows:

n	Justification
0, 48	Left justification
1, 49	Centering
2, 50	Right justification

ESC c 3 n

[Name] Select paper sensor(s) to output paper-end signal

[Format] ASCII ESC c 3 n
Hex 1B 63 33 n
Decimal 27 99 51 n

[Range] $0 \leq n \leq 255$

[Default] $n = 0$

[Description] Selects whether to output paper-end signal to a parallel interface or not when a paper-end is detected by the sensor selected, using n as follows:.

Bit	Off/On	Hex	Decimal	Function
0	Off	00	0	Paper roll near-end sensor disabled.
	On	01	1	Paper roll near-end sensor enabled.
1	Off	00	0	Paper roll near-end sensor disabled.
	On	02	2	Paper roll near-end sensor enabled.
2	Off	00	0	Paper roll end sensor disabled.
	On	04	4	Paper roll end sensor enabled.
3	Off	00	0	Paper roll end sensor disabled.
	On	08	8	Paper roll end sensor enabled.
4 ~ 7	Off	00	0	Reserved.

ESC d n

[Name] Print and feed n lines

[Format] ASCII ESC d n
Hex 1B 64 n
Decimal 27 100 n

[Range] $0 \leq n \leq 255$

[Default] Prints the data in the print buffer and feeds n lines.

ESC e n

[Name] Print and reverse feed n lines

[Format] ASCII ESC e n
Hex 1B 65 n
Decimal 27 101 n

[Range] $0 \leq n \leq 255$

[Description] Prints the data in the print buffer and feeds n lines in the reverse direction.

ESC p m t1 t2

[Name]	Generate pulse
[Format]	ASCII ESC p m t1 t2 Hex 1B 70 m t1 t2 Decimal 27 112 m t1 t2
[Range]	m = 0, 1, 48, 49 0 ≤ t1 ≤ 255 0 ≤ t2 ≤ 255
[Description]	Outputs the pulse specified by t1 and t2 to connector pin m to open the chash drawer, as follows:

m	Function
0, 48	Drawer kick-out connector pin 2.
1, 49	Drawer kick-out connector pin 5.

- t1 specifies the pulse ON time as [t1 × 2 ms].
- t2 specifies the pulse OFF time as [t2 × 2 ms].



Note:

For the TM-U230:
If t1 < 50, t1 should be 50. If t2 < 50, t2 should be 50.

For the TM-U210; If t2 < 50, t2 should be 50.

ESC r n

[Name]	Select printing color
[Format]	ASCII ESC r n Hex 1B 72 n Decimal 27 114 n
[Range]	0 ≤ n ≤ 1, 48 ≤ n ≤ 49
[Default]	n = 0
[Description]	Selects the printing color specified by n <ul style="list-style-type: none">• When n = 0,48, color 1 is selected.• When n = 1,49, color 2 is selected.



Note:

For the TM-J2100/2000, it is recommended to obtain the ESC/POS® Application programming Guide (ESC/POS® APG), which describes the recommended operation for 2 color printing control.

ESC t n

[Name]	Select character code table
[Format]	ASCII ESC t n Hex 1B 74 n Decimal 27 116 n
[Range]	Except for Thai model: $0 \leq n \leq 5, 16 \leq n \leq 19, n = 255$ For Thai model: $0 \leq n \leq 5, 16 \leq n \leq 26, n = 255$
[Default]	Except for Thai model: $n = 0$ For Thai model: $n = 20$
[Description]	Selects a page n from the character code table.

n	Selected character code
0	PC437 (USA: Standard Europe)
1	Katakana
2	PC850 (Multilingual)
3	PC860 (Portuguese)
4	PC863 (Canadian-French)
5	PC865 (Nordic)
16	WPC1252
17	PC866 (Cyrillic #2)
18	PC852 (Latin 2)
19	PC858 (Euro)
20	Thai character code 42
21	Thai character code 11
22	Thai character code 13
23	Thai character code 14
24	Thai character code 16
25	Thai character code 17
26	Thai character code 18
254	User-defined page
255	User-defined page

($20 \leq n \leq 26$) is supported only by the Thai model.



Note:

For the TM-L60II: The range is $0 \leq n \leq 5, n = 255$

For the TM-U230: The range is $0 \leq n \leq 5, n = 19, 254, 255$

For the TM-U210: The range is $0 \leq n \leq 5, 19 \leq n \leq 26, n = 254, 255$

GS B n

[Name] Turn white/black reverse printing mode on/off

[Format] ASCII GS B n
 Hex 1D 42 n
 Decimal 29 66 n

[Range] $0 \leq n \leq 255$

[Default] $n = 0$

[Description] Turns white/black reverse printing mode on or off.

- When the LSB of n is 0, white/black reverse mode is turned off.
- When the LSB of n is 1, white/black reverse mode is turned on.

GS V m**(Function A)****GS V m n****(Function B)**

[Name] Select cut mode and cut paper

[Format] ASCII GS V m (Function A)
 Hex 1D 56 m
 Decimal 29 86 m
 ASCII GS V m n (Function B)
 Hex 1D 56 m n
 Decimal 29 86 m n

[Range] $0 \leq n \leq 255$

(Function A) $m = 0, 1, 48, 49$

(Function B) $m = 65, 66$

[Description] Cuts paper in the specified mode.

	m	Function
Function A	0, 48	Executes a full cut (cuts the paper completely).
	1, 49	Executes a partial cut (one point left uncut).
Function B	65	Feeds paper to (cutting position + $n \times$ vertical motion unit) and executes a full cut (cuts the paper completely).
	66	Feeds paper to (cutting position + $n \times$ vertical motion unit) and executes a partial cut (one point left uncut).

- The paper is completely or partially (with one point left uncut) cut depending on the printer model.

GS h n

[Name] Select bar code height

[Format] ASCII GS h n
 Hex 1D 68 n
 Decimal 29 104 n

[Range] $1 \leq n \leq 255$

[Default] $n = 162$

[Description] Selects the height of the bar code as n dots.

① **GS k m d1...dk NUL**

② **GS k m n d1...dn**

[Name] Print bar code

[Format] ASCII ①GS k m d1...dk NUL
 Hex ①1D 6B m d1...dk 00
 Decimal ①29 107 m d1...dk 0
 ASCII ②GS k m n d1...dn
 Hex ②1D 6B m n d1...dn
 Decimal ②29 107 m n d1...dn

[Range] ① $0 \leq m \leq 6$ (k and d depend on the bar code system used)
 ② $65 \leq m \leq 73$ (n and d depend on the bar code system used)

[Description] Selects a bar code system and prints the bar code.

For ①

m	Bar Code System	Range of k	Range of d
0	UPC-A	$11 \leq k \leq 12$	$48 \leq d \leq 57$
1	UPC-E	$11 \leq k \leq 12$	$48 \leq d \leq 57$
2	JAN13(EAN13)	$12 \leq k \leq 13$	$48 \leq d \leq 57$
3	JAN8(EAN8)	$7 \leq k \leq 8$	$48 \leq d \leq 57$
4	CODE39	$1 \leq k$	$48 \leq d \leq 57, 65 \leq d \leq 90,$ $d = 32, 36, 37, 43, 45, 46, 47$
5	ITF	$1 \leq k$ (even number)	$48 \leq d \leq 57$
6	CODABAR (NW7)	$1 \leq k$	$48 \leq d \leq 57, 65 \leq d \leq 68,$ $d = 36, 43, 45, 46, 47, 58$

For ②

m	Bar Code System	Range of n	Range of d
65	UPC-A	$11 \leq n \leq 12$	$48 \leq d \leq 57$
66	UPC-E	$11 \leq n \leq 12$	$48 \leq d \leq 57$
67	JAN13(EAN13)	$12 \leq n \leq 13$	$48 \leq d \leq 57$
68	JAN8(EAN8)	$7 \leq n \leq 8$	$48 \leq d \leq 57$
69	CODE39	$1 \leq n \leq 255$	$48 \leq d \leq 57, 65 \leq d \leq 90,$ $d = 32, 36, 37, 43, 45, 46, 47$
70	ITF	$1 \leq n \leq 255$ (even number)	$48 \leq d \leq 57$
71	CODABAR (NW7)	$1 \leq n \leq 255$	$48 \leq d \leq 57, 65 \leq d \leq 68,$ $d = 36, 43, 45, 46, 47, 58$
72	CODE93	$1 \leq n \leq 255$	$0 \leq d \leq 127$
73	CODE128	$2 \leq n \leq 255$	$0 \leq d \leq 127$



Note:

Refer to the ESC/POS[®] Application Programming Guide (ESC/POS[®] APG) for details of printing barcode.

4 Sample Program (Basic)

```
PRINT #1, CHR$(&H1B);"@"; 'Initializes the printer (ESC @)

PRINT #1, CHR$(&H1B);"a";CHR$(1);'Specifies a centered printing position (ESC a)
PRINT #1, CHR$(&H1B);"!";CHR$(0); 'Specifies font A (ESC !)
PRINT #1, "January 14, 2002 15:00";
PRINT #1, CHR$(&H1B);"d";CHR$(3); 'Prints and 3 line feeding (ESC d)

PRINT #1, CHR$(&H1B);"a";CHR$(0); 'Selects the left print position (ESC a)
PRINT #1, CHR$(&H1B);"!";CHR$(1); 'Selects font B
PRINT #1, "TM-U210B          $20.00";CHR$(&HA);
PRINT #1, "TM-U210D          $21.00";CHR$(&HA);
PRINT #1, "PS-170           $17.00";CHR$(&HA);
PRINT #1, CHR$(&HA);          'Line feeding (LF)

PRINT #1, CHR$(&H1B);"!";CHR$(17); 'Selects double-height mode
PRINT #1, "TOTAL            $58.00"; CHR$(&HA);
PRINT #1, CHR$(&H1B);"!";CHR$(0); 'Cancels double-height mode

PRINT #1, "-----";CHR$(&HA);
PRINT #1, "PAID             $60.00";CHR$(&HA);
PRINT #1, "CHANGE           $ 2.00";CHR$(&HA);

PRINT #1, CHR$(&H1D);"V";CHR$(66);CHR$(0); 'Feeds paper & cut

'Drawer Kick (ESC p)
PRINT #1, CHR$(&H1B); CHR$(&H70); CHR$(&H0); CHR$(60); CHR$(120);
```

```
January 14, 2002 15:00

TM-U210B          $20.00
TM-U210D          $21.00
PS-170           $17.00

TOTAL            $58.00
-----
PAID             $60.00
CHANGE           $ 2.00
```

Print image

5 Serial Connection

When the TM printer is connected to the host PC with a serial interface, the usable serial cross cable is as follows:

D-Sub 25P(TM)			D-Sub 9P(PC)	
Pin No	Signal		Signal	Pin No
1	FG		DCD	1
2	TXD		TXD	3
3	RXD		RXD	2
20	DTR		DTR	4
6	DSR		DSR	6
4	RTS		RTS	7
5	CTS		CTS	8
7	GD		GD	5
25	RESET		RI/RESET	9

6 Self-test Mode

In self-test mode, the following items are checked and printed out:

- Control software version
 - DIP switch settings
- And others.

Use the following procedure to start a self-test.

1. To start the selftest, hold down the FEED button (*1)(*2) and turn on the printer with the roll paper cover closed.



Note:

(*1) For the TM-J2000/2100, hold down the PAPER FEED button instead of the FEED button.

(*2) For the TM-L90, keep holding down the FEED button until the ERROR LED comes on.

2. After printing the current printer status, the printer prints the message to show the standby state; then the paper out LED blinks. The printer is now in the self-test wait mode.
3. To start a test print, press the FEED button when the printer is in the self-test wait mode.
4. Make sure that the following message is printed.

***** completed *****